

Appln No. 10/089,406
O. Colette et al.
Office Action dated May 16, 2005

This listing of claims will replace all prior versions and listing of claims in the application.

LISTING OF CLAIMS

1. (cancelled)

2. (cancelled)

3. (currently amended) Protection device according to Claim 1, wherein the electrical component is a motor, and the control unit (10) is interposed between the electrical source (2) and the electrical component (4), and in that the control unit (10) modifies at least one characteristic the frequency of an electric current which supplies the electrical component (4) to limit the quantity of energy supplied to the electrical component by the electrical source (2).

4. (currently amended) Device for protecting an electrical source capable of powering at least one electrical component (4), wherein the device comprises a test unit (6) capable of delivering a signal (8) representative of a level of availability of the electrical source (2) to a control unit (10), the control unit (10) determining an operating mode of the electrical component (4) in which the consumption of electrical energy of the electrical component depends on the availability signal (8) received from the test unit (6), wherein the control unit (10) is

Appln No. 10/089,406
O. Colette et al.
Office Action dated May 16, 2005

interposed between the electrical source (2)
and the electrical component (4), and in that
the control unit (10) modifies at least one
characteristic of an electric current which
supplies the electrical component (4) to limit
the quantity of energy supplied to the
electrical component by the electrical source
(2) ~~Protection device according to Claim 3,~~
wherein the control unit (10) includes an
inverter (12), applying an electric current of
variable frequency to the electrical component
(4), and of a control circuit (20) of the
inverter (12), the control circuit comprising
an assembly of resistors (28) interposed
between a ground terminal (22) and a maximum
voltage terminal (24) of the inverter, the
assembly of resistors (28) having a plurality
of connection terminals (32, 36, 50, 52)
capable of being connected to an intermediate
terminal (26) of the inverter (12) via a
control line (62) provided with adjustment
means (60), the availability signal (8)
delivered by the test unit (6) being supplied
to the adjustment means (60) such that the
adjustment means connects the intermediate
terminal (26) of the inverter to a connection
terminal (32, 36, 50, 52) of the assembly of
resistors (28) determined according to the
availability signal (8).

5. (previously presented) Protection
device according to claim 4, wherein the
assembly of resistors (28) includes a divider
bridge having a plurality of resistors (44,
46, 48) and connection terminals (32, 36, 50,
52) disposed between each of the plurality of

Appln No. 10/089,406
O. Colette et al.
Office Action dated May 16, 2005

resistors and adjacent opposite ends of the plurality of resistors, the adjustment means (60) connecting the control line (62) to one of the connection terminals (32, 36, 50, 52) according to the availability signal (8).

6. (previously presented) Protection device according to Claim 5, wherein the divider bridge comprises two resistors (44, 46) having a node (50) disposed there between, and the adjustment means (60) includes a first switch (70) having a normal operating position in which the control line (62) is connected directly or by the intermediary of a protective resistor (40) to the maximum voltage terminal (24) of the inverter (12) in order to allow a normal operating mode of the electrical component (4), and a degraded operation position in which the control line (62) is connected to the node (50) of the divider bridge in order to allow a degraded operating mode of the electrical component (4), and by a second switch (72) having a closed position in which the control line (62) is connected to the ground terminal (22) of the inverter (12) in order to prohibit the operation of the electrical component.

7. (previously presented) Control device according to Claim 6, wherein the assembly of resistors (28) comprises a potentiometer (90) having end terminals (32, 50) connected to the maximum voltage terminal (24) and to the ground terminal (22) of the inverter, and a slider terminal (92) connected to the

Appln No. 10/089,406
O. Colette et al.
Office Action dated May 16, 2005

intermediate terminal (26) of the inverter by the intermediary of the first switch (70) when the first switch is in its closed position, and a manual control (94) device adjustable by an operator and capable of controlling the potentiometer (90) directly or indirectly.

8. (previously presented) Control device according to Claim 7, wherein the two resistors (44, 46) of the divider bridge (28) are separate from the potentiometer (90).

9. (previously presented) Control device according to Claim 7, wherein the potentiometer (90) constitutes one of the two resistors (44, 46) of the divider bridge.

10. (previously presented) Control device according to one of Claim 7, wherein the electrical component is an electric motor (4) driving a compressor of an air-conditioning system and the manual control device (94) obtains a continuous adjustment of the speed of the motor between a minimum speed corresponding to a "warmest" mode and a maximum speed corresponding to a "coolest" mode.

11. (previously presented) Control device according to Claim 8, wherein the electrical component is an electric motor (4) driving a compressor of an air-conditioning system and in that the manual control (94) obtains a continuous adjustment of the speed of the motor between a

Appln No. 10/089,406
O. Colette et al.
Office Action dated May 16, 2005

minimum speed corresponding to a "warmest" mode and a maximum speed corresponding to a "coolest" mode.

12. (previously presented) Control device according to Claim 9, wherein the electrical component is an electric motor (4) driving a compressor of an air-conditioning system and in that the manual control (94) obtains a continuous adjustment of the speed of the motor and in that the manual control (94) is capable of obtaining a continuous adjustment of the speed of the motor between a minimum speed corresponding to a "warmest" mode and a maximum speed corresponding to a "coolest" mode.